



CON-SPACE

COMMUNICATIONS

Safety in Communication®

CBRN / WMD

Bio-Chemical

Decontamination

Hazmat Control

The **SRVA** Voice Amplifier Push-to-Talk Radio Accessory

The SRVA was developed by CON-SPACE as a new concept in radio accessory functionality; it combines a Two-Way Radio Accessory with a Voice Amplifier. The device can utilize any of the Armoury accessories to facilitate voice communication. The amplification function allows users to speak at normal levels and be understood while wearing full face or half mask respiratory protection, PAPR's or protective suits.

...continued on reverse >>

CON-SPACE
SRVA

www.con-space.com

SRVA VOICE AMPLIFIER RADIO ACCESSORY

.../ This makes it ideal for use in a wide range of applications including; Mass decontamination, Drug Lab Takedowns, Nuclear Reactors, Clean Rooms, Riot squads, EOD etc...

In addition, the SRVA incorporates the functionality of a portable two-way radio accessory into the same housing as the Voice Amplifier. It features a combination PTT Switch and Speaker Grill (patent pending) to provide the user with quick and easy access to their radio network. The unit can operate with virtually any make or model of portable radio.

The SRVA incorporates multiple glands, seals and gaskets into the carbon filled polycarbonate housing so the unit can be

washed, decontaminated and withstand heavy use. Standard features include on/off/volume control knob, visual dual colour power/ low battery indicator LED, unique CON-SPACE accessory quick connect, molded in Lanyard attachment point, 360 degree swivel belt clip, and Captive battery housing thumbscrews.

The SRVA is powered by three standard 'AA' batteries and will operate for up to 48 hours. (batteries included) Moreover, the SRVA includes a fail safe feature, whereby the portable radio function continues to operate when the batteries that power the voice amplifier are completely drained.

Primary Options

**All options connect to the SRVA via a "Quick Connect Cable" allowing for rapid attachment and detachment from the unit.*



**The SRVA CANNOT be ordered without a separate Radio Interface Cable*

Technical Specifications

Type of Product:	Voice Amplifier PTT
Type of Microphone:	Interchangeable
Speaker Material:	Mylar
Speaker Frequency Response:	450 Hz to 9 kHz
Push-to-Talk:	Tactile
Self-Powered:	Yes
Battery Type:	3x 1.5 V- AA cells
Battery Life Operator Standby:	40 / 200
Weight:	13.7 oz / 390g
Cable Pull Strength:	69 kg / 31 g
Colours:	Matte Black
Operating Temperature:	-20 C to 40 C
Output Sound Level Speech:	84 dB
Water Resistance:	Yes
Adjustable Mounting:	Yes
ROHS Compliance:	Yes
IP Compliance:	Yes, IP-57
EMC Compliance:	Yes
Warranty	18 Months
Part Number:	1920-03-000

Product Info

- Large Speaker & PTT
- Volume Control
- Fail Safe Operation
- Revolutionary Throat Mic Design
- Versatile Hearing Accessories
- Loud & Clear Voice Amplification
- Powered by 3 AA Batteries
- Low Battery Indicator
- Survives all weather conditions
- Easy to locate Speaker & PTT
- Use with any Make or Model of Facemask or Breathing apparatus
- Connects to most make/model radios
- Waterproof & Dust Tight
- 48 hours of Operating Time

CON-SPACE

COMMUNICATIONS

Safety in Communication®

Printed in Canada Feb 2008 SP017

Contact Info

North America Toll Free: 1 (800) 546 3405

Canadian Head Office
U.S. Sales Office
European Sales Office
Email

Tel (604) 244 9323

Tel (402) 477 0086

Tel +44 (0) 1636 642484

sales@con-space.com

Fax (604) 270 2138

Fax (402) 742 7880

Fax +44 (0) 1636 642485

Website

www.con-space.com